



**ATTENTION!**

**Note ESD protection!**

Do not touch on electrical parts because of ESD protection  
 - Take appropriate protections. Touch a grounded piece of metal as a minimum protection.

**Tips for installation of options boards**

**Attention:** Before opening the control device, please **separate all poles of the control device from the mains** (fuse box or distributing box).

Please plug the 4 included plastic distance bolts with the sharp edges in the provided holes on the control board. Now you can put the flat ribbon plug into the appropriate connector of the control board (coding nose up). Lead the connecting terminal through the separating strip and set the options board onto the distance bolts. Press the options board firmly, until the lock clips of the distance bolts click into place. The notches of the board must be placed firmly on the noses of the separating strip, otherwise the options board can slip from the fastener when attaching the power plugs.

**Installation instructions of the options board**

Prepared: Kanzinger 25.03.2010	Modified: Kanzinger 27.07.2022	Checked:	File: I:\Doku\Fasel\FCU-Ext-Modul\Opt_Plattinen_Einbau.cdr	Technical changes and errors excepted, illustration similar
--------------------------------------	--------------------------------------	----------	---	---

